

The NFO Sinus® frequency inverter is based on a patented Swedish technology that allows you to control the speed of electric motors without generating electromagnetic interference, which in turn offers a range of unique benefits. Thanks to the sine-wave voltage, the inverter is intrinsic EMC, i.e., it is interference-free in itself.

NFO®
Sinus

SIMPLE

Installation is easy and cost-efficient due to there is no need of shielded cables, EMC filters or other EMC-classed installation accessories. When undertaking energy efficiency projects, it's also possible to use the existing non-shielded cables, this makes the installation work quick, easy and cost-efficient. There is no cable length limitation between the motor and the NFO Sinus® except for the resistance of the cable. The NFO Sinus® can be installed where it's suitable depending on the application, even if the distance to the motor is several hundred meters thanks to the Sinus technique which gives cost-efficient flexible solutions in all environments.

SILENT

NFO Sinus® is interference free and therefore does not create any electromagnetic interference which can disturb surrounding equipment. The NFO Sinus® satisfies the most stringent demands set out in the EMC directive 2014/30/EU without filters and without shielded cables

and can be used in every kind of environment from industrial, medical to residential. With NFO Sinus® you also avoid all the disturbing switching noise in the motor, which results in a quieter environment.

SAFE

NFO Sinus® does not generate any bearing currents. The motor therefore has a longer lifespan. No earth leakage currents are generated, which means that residual current devices for both personal safety and fire prevention can be used. This provides a high level of electrical safety.

HIGH PRECISION

The motor speed is very precisely controlled and with full torque right from stand-still as well as at a low speed regardless of chosen control mode Speed, frequency, torque or process-control. The inverter furthermore has an energy-save function that allows you to conserve even more energy when running with a low load on the motor, e.g., fans, which at times run at a low speed.



Simple installation

- No shielded cables
- No complicated installation requirement
- No limitations of distance



Silent operation

- No electromagnetic interference
- No irritating switching noise



Safe technology

- No bearing currents
- No earth currents

NFO Sinus® is available in size 0,37 kW up to 22 kW

Power rating (kW)	7.5	11.0	15.0
Continuous Rating (A)	14.8	21.5	28.5
Maximum Rating (A)	17.7	25.8	32.0
Protection Class	IP20/IP54	IP20	IP20
Measurements HxDxW (mm)	413x280x150	413x280x150	413x265x203
Weight (kg)	14.0	14.0	14.0
Part number	NFO 2C1/3A3151D	NFO 2C1A3221D	NFO 2C1A3281D

	Voltage (V)	Frequency (Hz)
Input:	3x380-440V ±10%	50/60 Hz ± 10 %
Output:	0-440V + 10 %	0-150Hz
Output voltage wave form:	Sinus	
Operating mode:	4-kvadrant	
Control inputs configurable:	Setpoint	Actual value
2 pcs of voltage(V)	0-10V, 2-10V, ± 10V	0-10V, 2-10V, ± 10V
1 pc of current (mA)	0-20 mA, 4-20 mA ± 20 mA	0-20 mA, 4-20 mA ± 20 mA
1 pc of potentiometer input	Potentiometer 10 kΩ	
Selectable from terminal + or- logic	7 fixed setpoints	

Acceleration time:	0,2-500 s
Retardation time:	0,2-500 s
Relay outputs:	Common alarm (Potential free contact max 1A 50VDC) Run signal (Potential free contact max 1A 50VDC)
Voltage output:	24V supply to external sensor
Control modes:	Frequency control 0-150 Hz Speed control 0-9000 rpm Torque control 1-400% of nominal motor torque, depending on inverter capacity Process control PI- controller with feedback
Local mode keyboard:	Forward, Reverse, Stop
Motor protection:	Thermistor input PTC or Klixon Power guard Overload protection
Communication:	Modbus RTU/ASCII
Software:	Sinus Manager free download from www.nfodrives.se
Energysave function:	Optimized motors magnetizing current at low load.
Environment:	Ambient temp -10-> +40°C Storage temp -20->+60°C RH 0->90% non-condensing.
Earth current:	< 2 mA. RCD's for both person -and fireprotection can be used.
EMC:	Certified to be used without shielded cables and filters EMC Directive 2014/30/EU Standards: EMC Emission EN 61000-6-3:2007/A1:2011 EMC Immunity EN 61000-6-2:2005, EN 61000-4-2, -3, -4, -5, -6, -11 LVD EN 61800-5-1

Option

Expansion card I/O:	Input PT1000 Output 0-10V, Frequency 0-32 kHz open collector Function relay Potential free contact max 2A 50VDC 50W, 24V to external sensor
Brake resistors/chopper:	Dimensioning of braking resistors; see the user and installation manual Chap. 6
Communication card:	Can-open, Profi-Bus DP

For more information: See NFO Drives Operating and installation manual